



1-11-05

Improved anti clipping compressor for Motion Sound KP-200S models < SN526

1. Remove the Amplifier chassis as per owner manual and locate the power amplifier PC board.
2. The image below shows the left and right ends of the board where the modifications take place.
3. Remove diodes D1, D2, D3, and D4.
4. Remove Resistor R86 and R87. Replace each resistor with a pair of 1N4729 Zener Diodes soldered Cathode to Cathode (line to line marks on Diode.) See image below.
5. Remove Capacitors C57 and C62. Replace with 3.3 UFD 35V Non Polarized Electrolytic.



